

RML0649	BATTERY
----------------	----------------

1. Scope

This technical specification is for the product of RML0649 Li-ion rechargeable battery pack.

2. Cell Type

Cell: Sealed Li-ion prismatic cell 2pcs pack

3. Rating

Nominal Voltage: 7.4V V per pack

Nominal Capacity: 2000mAh

Charging: charge at the constant current of 400mA to 4.2V, then charge with 4.2V until the current approaching 20mA.

Discharge End Voltage: 6V per pack

Maximum Discharge: 4.0A Current

Weight: 120g

Charge Temperature: 5°C to 45°C

Discharge Temp: -20°C to 60°C

Storage Temperature: -20°C to 35°C

4. Physical Specification

Length: 110.2 mm

Width: 56.3mm

Height: 22.7mm

Maximum Overstep: 0.1mm

5. Electrical Test

5.1 Charging Characteristics

The battery pack should be charged under the following conditions:

--At a constant current of 400mA to 4.2V, then charge with 4.2V until the current approaching 20mA.

The above test is the ambient temperature of 20°C (+,-5°C)

5.2 Discharge Characteristics

After adopt the above charge procedure as 5.1 the battery pack is stored for 1 hour at the same temperature range, this is to be discharged at various current till the end voltage reaches 6V

--At 400mA discharge for 5hrs (0.2C)

--At 600mA discharge for 3.3hrs (0.3C)

--At 2000mA discharge for 54 minutes (1C)

--At 4.0A discharge for 25 minutes (2C)

5.3 Capacity Characteristics

The battery pack should be at or more than 90% minimum capacity under the above either charging or discharging procedure.

5.4 Charge retention

After stand charging procedure as per 5.1, the battery pack store for 28 days, then discharge the battery pack are 0.2C, the nominal capacity shall not be less than 85%.

--Before using, the battery pack shall be properly charged as 5.1.

--Keep the battery pack in cool and dry place.

--DO NOT throw the battery pack into fire or disassembles them.

--DO NOT short-circuit the battery pack

--DO NOT charge with more than specified current.

WARNING: This battery pack should be charged by proper specified charger .
After long storage, it is desirable to cycle (charge/discharge) the battery 3 times to restore full capacity.

The supplier reserves the right to modify product specification and data stated herein without prior notice.