



© Vdi Group photo

MAIN INFORMATION / INFORMATIONS GÉNÉRALES

BRAND	MARQUE	NX
TYPE OF BATTERY	TYPE DE BATTERIE	Compatible
TECHNOLOGY	TECHNOLOGIE	Nickel-métal hydrure
CAPACITY	CAPACITÉ	2200 mAh
VOLTAGE	TENSION	3,6 V
DIMENSIONS	DIMENSIONS	
• Length	• Longueur	59,9 mm
• Width	• Largeur	54,8 mm
• Height	• Hauteur	21,8 mm
WEIGHT	POIDS	105 g

ADDITIONAL INFORMATION / INFORMATIONS COMPLÉMENTAIRES

EAN CODE	CODE EAN	3660766447357
CELL TYPE	TYPE DE CELLULES	JJJ J-AA 1200A
CHARGING VOLTAGE AND CURRENT	TENSION ET COURANT DE CHARGE	4,2V - 5,7V / 0,2C - 2C
DISCHARGING VOLTAGE AND CURRENT	TENSION ET COURANT DE DECHARGE	3V / 0,2C - 2C
OPERATING TEMPERATURE	TEMPERATURE DE FONCTIONNEMENT	
• Charging	• Chargement	0°C + 40°C (32°F + 104°F)
• Discharging	• Décharge	0°C + 50°C (32°F + 122°F)
STORAGE TEMPERATURE	TEMPÉRATURE DE STOCKAGE	
• Short period	• Période courte	-20°C + 50°C (-4°F + 122°F)
• Long period	• Période longue	-20°C + 30°C (-4°F + 86°F)

COMPATIBLE PRODUCTS / PRODUITS COMPATIBLES*

Non-exhaustive list / Liste non exhaustive

FOR USE IN	UTILISER DANS	68300900
REPLACEMENT FOR	EN REMPLACEMENT DE	Hetronic Mini

www.enix-energies.com - 25/04/2024

OUTLINE SAFETY WARNING: USE ONLY WITH IN THE ALLOWED PARAMETERS. Do not short circuit or over-load the battery. Charge only using an approved charger designed specifically to charge this battery. Do not heat above maximum temperatures indicated. Never crush, mutilate, puncture or abuse the battery. Do not dismantle the pack or disable any of the protective devices or circuits. DO NOT USE THE BATTERY IF YOU SUSPECT IT MAY BE FAULTY OR DAMAGED.

© Copyright Enix Energies 2005. NB: This document and the product design are the intellectual property of Enix Energies. No document or design may be copied or used for commercial purposes without written permission of Enix Energies. Users must satisfy themselves, by means of testing etc., that products are suitable for their application. Data in this document is for general guidance only; consult cell manufacturers data for definitive information. Information is given free of charge and in good faith, but no responsibility can be accepted for any errors or omission or costs or losses or liabilities arising from the use of this information. All business is conducted to Enix Energies terms and conditions only.

